

FCD7000 Series - INSTALLATION INSTRUCTIONS

CAUTION: BEFORE CONNECTING THE LUMINAIRE TO A POWER SUPPLY, MAKE SURE THE POWER IS SWITCHED OFF.

J-BOX RECOMMENDATION: NEMA 6P Rated Box to be provided by others.

GENERAL:

1. Before starting the installation, make sure all electricity has been turned off and electrical breaker has been locked out and tagged out.
2. To ensure the success of the installation, be sure to read these instructions and review the diagrams thoroughly before beginning.
3. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code.

NOTE: The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur.

For Lamp Replacement (Fluorescent Only):

First remove Luminaire from Housing grade by loosening the lock mechanism screw. Now locate the end of Luminaire with power cord and remove lock mechanism screw. Then remove screws from same end of Luminaire. Pull out on end cap to slide the lamp tray out of Luminaire. Replace lamps. Reverse these steps for reassembly and follow steps 3 thru 7 on page 1 to reinstall Luminaire into Housing grade.

IMPORTANT: All FC and SSL products can be cleaned with non-abrasive and chemical free agents. Use a soft cloth with mild detergent on exterior only.



DETAILED ILLUSTRATION

